

DS-UPS1000-R
1000VA/600W, Backup UPS with built-in battery



- Built-in AVR
- Auto restart while AC is recovering
- Super fast charging
- Wide input voltage range
- Overload protection
- Short circuit protection
- Surge protection

▪ Specification

Power	
UPS Capacity	1000 VA / 600 W
Input	
Input Voltage Range	DS-UPS1000-R: 140 VAC to 290 VAC DS-UPS1000-R(海外标配)/英标/万用座(E),DS-UPS1000-R(海外标配)/欧标/万用座(E):140 VAC to 300 VAC DS-UPS1000-R(海外标配)/德标/德标:162 VAC to 268 VAC (220V) 170 VAC to 280 VAC (230V) 177 VAC to 290 VAC (240V)
Input Frequency	50/60 Hz self-adaptive
Plug Type	DS-UPS1000-R(海外标配)/英标/万用座(E):UK TYPE G DS-UPS1000-R(海外标配)/欧标/万用座(E),DS-UPS1000-R(海外标配)/德标/德标:Schuko
Output	
Output Voltage Range	DS-UPS1000-R:210 VAC to 235 VAC DS-UPS1000-R(海外标配)/德标/德标:220/230VAC ± 10% DS-UPS1000-R(海外标配)/英标/万用座(E),DS-UPS1000-R(海外标配)/欧标/万用座(E):230VAC ± 10%
Output Frequency	50/60 Hz ± 0.5 Hz self-adaptive
Transfer Time	≤ 10 ms
Waveform	PWM
Outlet Type	DS-UPS1000-R(海外标配)/英标/万用座(E),DS-UPS1000-R(海外标配)/欧标/万用座(E):Universal DS-UPS1000-R(海外标配)/德标/德标:Schuko
Outlet Number	2
Battery	
Battery Type	12 V/9 Ah x 1, lead-acid battery
Recharge Time	4-6 hours recover to 90% capacity
Typical Backup Time	Run time at 100w: 20-25 min
Interface	
Communicate Ports	No
Protection	
Full Protection	Surge protection, Overload protection, Discharge protection, Short circuit protection
Indicator	
Display	LED indicator Line mode: Solid green led lighting Battery mode: Solid yellow led flash Fault mode: Solid red led lighting
Alarm	Charging Mode (DC mode): Sounding every 8 seconds Low Battery: Sounding every second Overloading Mode: Sounding every 0.5 seconds Fault: Continuously sounding

General	
Operating Temperature	0 °C to 40 °C (32 °F to 104 °F)
Operating Humidity	0% to 90% (non-condensing)
Dimension	276.1 mm × 101 mm × 142 mm (10.9" × 3.98" × 5.59")
Weight	DS-UPS1000-R:Approx. 5.4 kg (11.9 lb) DS-UPS1000-R(海外标配)/德标/德标:Approx. 5.55 kg (12.24 lb) DS-UPS1000-R(海外标配)/英标/万用座(E),DS-UPS1000-R(海外标配)/欧标/万用座(E):Approx. 4.76 kg (10.5 lb)

▪ Available Model

DS-UPS1000-R/UK/Uni(E)

DS-UPS1000-R/Uni(E)

DS-UPS1000-R

See Far, Go Further



www.hikvision.com
support@hikvision.com

